XD007

便携式移动外置光驱

使用说明

感谢您选择ORICO!
在您使用本产品前，请仔细阅读这份用户使用说明书！

产品介绍

本产品是一款支持刻录 DVD/CD 的便携式移动外置光驱，可以解决电脑光驱读取速率慢，电脑无光驱或光驱损坏而无法读盘的问题。产品具备空盘刻录视频、音频文件等功能，采用USB3.0接口读刻效率更稳定，使用更广泛，是您办公，居家，娱乐的好助手。

产品特点

1. 隐藏式双USB设计，适用于适用于USB2.0/3.0/Type-C接口台式机或笔记本电脑。
2. 无需安装驱动程序，即插即用。
3. 数据线采用纯铜编织工艺，抗干扰能力强，信号衰减，数据传输更加稳定。

包装清单

产品本体 1个
电源线 1根
说明书 1本
感谢卡 1张


产品规格

产品名称	便携式移动外置光驱
产品型号	XD007
产品尺寸	157(L) x 147(W) x 26(H)mm
接口	USB3.0 双接口 (Type-C+Type-A)
读取速度	CD-ROM:24X, DVD-ROM:8X
刻录速度	CD-R:24X, CD-RW:16X, DVD-R:8X, DVD-RW:16X
支持读取类型	DVD ROM (单层), DVD ROM (双层), DVD+R/DVD-R,DVD+R DL/DVD-R DL, DVD+RW/DVD-RW, DVD RAM, ROM/finalized CD RW, Data/CD-DAE, Video CD, finalized CD RW, Unfinalized CD-R/RW
支持刻录类型	CD-R, CD-RW,DVD-R,DVD-RW
支持刻录模式	For CD-R/RW DVD-R/DVD-RW disc: 1. Disc At Once(DAO) 2. Session At Once(SAO) 3. Track At Once(TAO) 4. Variable Packet Write 5. Fixed Packet Write
支持系统	Windows XP/2003/Vista/7/8.1/10, Linux, Mac OS
产品供电	USB供电, 配 0.5m Type-A转Mirco供电线

使用方法

Windows 7下的驱动安装说明

1. 将外置光驱的数据线连接到电脑USB接口，电脑显示器右下角有提示，系统会自动安装程序，等待安装完成。
2. 点击桌面上的“**计算机**”，在“**有可移动的存储设备**”中可找到光驱盘。



3. 双击光驱盘，或右键单击并选择“**弹出**”，会跳出装入光盘提示。



4. 当光驱弹出，装入光盘后，外置光驱的指示灯亮起，说明正常工作。
5. 刻录功能，需要自行安装刻录软件进行刻录。

注：如果发现外置光驱读写不够顺利时，请外接5V电源适配器（需自配）。

常见问题

外置光驱无法使用怎么办?

1. 请确保正确安装，安装时请暂时关闭杀毒软件。
2. 尝试更换电脑其他USB接口。
3. 避免使用USB延长线和HUB连接本产品，以免导致电脑无法识别。
4. 无法读盘：检查光盘是否正确放入，清洁光盘，更换其它光盘或拿新盘测试。
5. 能读出光盘内容，不能播放，请更换播放软件。
6. 读碟出现异响，声音大（1.更换几张光盘试试，2.光盘没有卡好，3.光盘质量差，薄厚不同也会影响到声音大小）。

注意事项

1. 产品内部有激光光源可能对眼睛有害，请不要直视。
2. 请勿将产品及附件放置于具有强大电磁场的器具中，以及远离磁性设备。
3. 请将机器平稳的放在桌面上，切勿放在不稳定的物品上。
4. 请勿将机器放在易受挤压的地方，以保证机器正常使用。
5. 请勿撞击、扔掷、针刺本产品，并避免跌落、挤压、弯曲产品。
6. 请勿擅自拆卸和维修产品及附件，只有授权机构才可维修本产品。
7. 本产品使用过程中如有任何问题，可随时与您的经销商或ORICO客户服务中心联系。

保修说明

保修条例

ORICO 产品的售后服务严格依据《中华人民共和国消费者权益法》、《中华人民共和国产品质量法》，实行售后三包服务，服务内容如下：

1. 自签收日起 7 日内，产品出现性能故障并由ORICO客户服务中心鉴定之后，可享受退货、换货或免费维修服务。
2. 自签收日起 8-15 日内，产品出现性能故障并由ORICO客户服务中心鉴定之后，可享受换货或免费维修服务。
3. 自签收日起 12 个月内，产品出现性能故障并由ORICO客户服务中心鉴定之后，可享受免费维修服务。

保修限制条款

深圳市元创时代科技有限公司保修条款不适用于以下情况：

1. 超过保修条款期限。
2. 未经授权拆解、改动或维修过的产品，以及碰撞、进液、摔坏等人为损坏。
3. 水灾、火灾、雷击、地震等不可抗力造成的损坏。
4. 与本使用说明不一致的错误操作。
5. 产品或包装盒条码与实物不符，以及被涂改、撕毁。
6. 未经授权使用非原装配件造成的损坏。
7. 无有效的购买凭证。

声明

深圳市元创时代科技有限公司，版权所有
感谢您购买ORICO产品，为了更好的使用本产品的所有功能，请您在使用产品之前仔细阅读本使用说明介绍的产品功能、使用说明以及注意事项。
ORICO®为深圳市元创时代科技有限公司注册商标。
本使用说明中提及的其他所有产品名称、商标、服务名称和公司名称，由其各自的所有者拥有。
本使用说明所提及的信息仅供参考，深圳市元创时代科技有限公司保留随时修改本使用说明中任何信息的权利，无需提前通知。除非有特殊约定，本使用说明仅作为使用指导，本使用说明中的所有陈述、信息等均不构成任何形式的担保。深圳市元创时代科技有限公司不对因使用本使用说明相关内容及本使用说明描述的产品而产生的任何特殊的、附带的、间接的、继发性的损害进行赔偿，也不对任何利润、数据、商誉或预期节约的损失进行赔偿。在相关法律允许的范围内，在任何情况下，深圳市元创时代科技有限公司对您因为使用本使用说明描述的产品而遭受的损失的最大责任（除在涉及人身伤害的情况中根据适用的法律规定的损害赔偿外）以您购买本产品所支付的价款为限。

官方网站　　Website

发行版本: XD007-MUG-R0
制 造 商: 深圳市元创时代科技有限公司
Manufactured by ORICO Technologies Co., Ltd.
电话/Tel: 86-755-25196059
邮箱/E-mail: supports@orico.com.cn
官方网站: www.orico.com.cn
Official Website: www.orico.cc
公司地址: 深圳市龙岗区布吉街道甘李工业园甘李六路12号中海信创新产业城14A栋903-904
Company Add : 903-904, 14A, Zhonghaixin Innovation Industrial Park, 6th Gan Lee Road, Buji, Longgang District, Shenzhen, China
工厂地址: 东莞市常平镇塘角路24号元创动力(ORICO)互联网产业园
Factory Add : ORICO Internet Oriented Industrial Park, No.24 Tangjiao Rd, Changping County, Dongguan, China

XD007

Portable USB3.0 Interface Drive

User Manual

Thank you for choosing ORICO products!
Please read this user manual carefully before using.

Product Introduction

This product is a portable USB external drive which support to burning DVD/CD, able to solve the problem of slow reading of computer optical drive, or unable to read the disk due to no optical drive. It adopted USB3.0 interface, more stable and faster to burning files like vedio, audio, etc. It can perfectly meet your needs of working and playing.

Product Features

1. The insides dual USB design, suitable for USB2.0/3.0/Type-C interface desktop and tablet.
2. Drive-free, plug and play.
3. The cable adopts fine-cupper braid, strong anti-interference, more stable to data transferring.

What's in the box

Portable USB3.0 Interface Drive 1PCS
Power Cable 1PCS
User Manual 1PCS
Service Card 1PCS


Specifications

Name	Portable USB3.0 Interface Drive
Model	XD007
Dimension	157(L) x 147(W) x 26(H)mm
Interface	USB3.0 (Type-C+Type-A)
Reading speed	CD-ROM:24X, DVD-ROM:8X
Burning speed	CD-R:24X, CD-RW:16X, DVD-R:8X, DVD-RW:16X
Read types	DVD ROM (Single layer), DVD ROM (Dual layer), DVD+R/DVD-R, DVD+R DL/DVD-R DL, DVD+RW/DVD-RW, DVD RAM, ROM/finalized CD RW, Data/CD-DAE, Video CD, Finalized CD RW, Unfinalized CD-R/RW
Burn types	CD-R, CD-RW,DVD-R,DVD-RW
Burning mode	For CD-R/RW DVD-R/DVD-RW disc: 1. Disc At Once(DAO) 2. Session At Once(SAO) 3. Track At Once(TAO) 4. Variable Packet Write 5. Fixed Packet Write
Supported System	Windows XP/2003/Vista/7/8.1/10, Linux, Mac OS
Power Supply	USB-powered，enclosed with Type-A to Mirco power cable, Length: 0.5m


How to use

Instructions for Windows 7 Driver Installation

1. Connect the cable with external optical drive to USB port. When there is a hint on the bottom right, windows will start installing.
2. Click **"Windows"**, then the optical disc will be found in **"Removable Storage"**.



3. Double click optical drive, or choose **"pop-up"**, then windows will advise you to load optical disc.



4. After installing optical disc when optical drive pops up, external optical drive lightens, which means it works well.
5. Disc burning function need to be used with burning software.

PS: If the external drive works under expectation, please connect 5V power adapter. (Need purchase separately)

FAQ

What if external drive runs poor?

1. Please make sure install correctly, turn off anti-virus software during installation.
2. Try to replace other USB ports.
3. Avoid using USB expanded cables and HUB for connecting, in case the computer doesn't recognize it.
4. Failed reading: (a)Check whether the disc is properly placed. (b)Clean disc. (c)Replace another disc or testing with new disc.
5. If the optical disc can be read but not be played, please change the play software.
6. If there is noise when reading, please (a)Change optical discs.(b)Check the installed optical disc. (c)Check the quality of optical discs, which will influence the sound.

Attention

1. Do not look steadily for the laser source doing harm to eyes.
2. Do not put the product or accessories in a device with a strong electromagnetic field and be away from magnetic equipment.
3. Please place the machine on the table smoothly.
4. Do not place the machine on which it squeezes easily, for its normal use.
5. Do not strike, throw, prick, drop, compress, or bend.

6. Do not disassemble and repair products and accessories without authorization, only for authorized organization.
7. If there are any problems in the use of this product, please contact with dealers or ORICO customer service center.

Declaration

ORICO Technologies Co., Ltd., all rights reserved.
Thank you so much for purchase ORICO product. Please refer to this manual when using orico product or experienced issues. Additionally, please kindly contact ORICO customer care team if any concern.
ORICO® is registered trademark of ORICO Technologies Co., Ltd.. Any other product, trademark, service or company mentioned herein is trademark or registered trademark of the respective owners.
This manual is for reference only and it's not a guarantee. ORICO Technologies Co., Ltd. reserve all rights of maintenance to this manual and shall not liable for any lost or damage resulting from this manual. Please kindly contact orico customer care team when any concern. ORICO Technologies Co., Ltd shall not liable for compensation and maintenance of the following conditions.
1. Any special, incidental, indirect and secondary lost or damage.
2. Profit and revenue lost or damage.
3. Files, data, drive and device lost or damage.
Note: Compensation for lost or damage resulting from this manual or orico product shall not exceed the payment of your purchase to this product.

FCC

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.